ZM6500USB

6 ZONE USB MIXER AMPLIFIER

Features



- Public address (PA) 6 zone commercial mixer power amplifier
- 19” rack mount amplifier of 2U height
- Rated output of 500W
- 6 zone speaker outputs of 100V
- Single zone 100V/70V/4-16 Ohm speaker outputs
- Six zone speaker outputs with independent volume control
- Built-in media player with MP3/USB/FM tuner/Bluetooth
- Mic1 input 6.3mm jack with VOX highest priority
- Mic/Line input 2-4 balanced XLR with mic/line switch and +48V phantom power selector
- Line 4-5 inputs on rear panel by RCA
- EMC input by RCA on rear panel with secondary priority except MIC1
- One amplifier capacity of 6 remote paging microphones DA-500RM up to 300 meters
- Volume control for Mic1-4 and line 1-2, bass/treble/master and 6 zone volume control on front panel
- Visual indicators include AC and DC Power, protection, clip, 6 zone status and output level meters
- Complete amplifier protection includes overload, clip, short circuit and high temp protection
- 230V AC and 24V DC operation system

Technical Specifications

Feature	Specification
Description	6 Zone Mixer Amplifier with MP3/USB/FM tuner/Bluetooth
Rated Power Output	500W
Speaker Output	6 zone speaker outputs of 100V Single zone 100V/70V/4-16 Ohm speaker outputs
Input	Mic1-4: 2.5mV, Mic1 of 6.3mm jack, Mic/line 2-4 of balanced XLR Line1-2: 250mV, RCA EMC: 250mV , RCA
Frequency Response	80-16KHz
THD	<0.1%
S/N Ratio	>70dB
Protection	High temp, short circuit, clip & overload protection
Power Supply	230V AC & 24V DC, 50-60Hz
Power Consumption	500W
Dimension	484×405×88mm
Weight	10.4kg

71 - 75 Shelton Street Covent Garden WC2H 9JQ LONDON U.K.
+44 204 577 07 66
info@lucasacs.co.uk